


# Quick Start Guide

1

**POWER ON SENTRY K300** Hold  key for 3 seconds.  
(If the battery is low or dead, charge by plugging into a certified USB port for 30 min.)

2

## ENTER PASSWORD\* WHEN PROMPTED

Selected character is shown in the white circle on the screen.  
Press key repeatedly within one second to switch characters.



Press



to delete and



to enter

\*Enter default password **12345667** on first use  
(default password can be used 3 times before it MUST be changed)

3

Go to menu, scroll down to SafeConsole and press enable. Then go back to menu and press CONNECT. \*This step may already be done by your administrator.



4

Once the Sentry K300 is connected to the computer, you will get the "SafeConsole Waiting..." message on the screen.

5

After a few seconds, Windows will display an AutoPlay window, click run "UnLocker" and the device client app will open.



At the SafeConsole Connection Token URL screen, enter your connection URL to register this Sentry K300 to your SafeConsole server.\*Refer to connection guide that will be provided by SafeConsole Administrator.

For more info visit [datalocker.com/k300](https://datalocker.com/k300)